


## NOTES:

- 1. FOR HAND INSERTION USE SPACING 0.130 [3.30] FOR AUTOMATED INSERTION USE SPACING 0.135 [3.43]
- 2. HEX NUT AND FLAT WASHER SUPPLIED UNASSEMBLED.
- 3. MATERIAL: HOUSING, HEX NUT - COPPER ALLOY, NICKEL PLATED INSULATOR HOUSING - THERMOPLASTIC TERMINAL INSULATORS - PHENOLIC FLAT WASHER - STEEL, NICKEL PLATED PIN, SPRING, TERMINALS - COPPER ALLOY, SILVER PLATED
- 4. IT IS RECOMMENDED THAT THE JACK MOUNTING NUT BE TIGHTENED SNUG BY HAND BEFORE APPLYING A FINAL TIGHTENING TORQUE OF 8-10 IN-LBS USING HAND TOOLS ONLY. POWER DRIVER OR IMPACT DRIVERS ARE NOT RECOMMENDED.
- 5. THESE PRODUCTS ARE RoHS COMPLIANT



BY SWITCHCRAFT INC. AND IS RELEASED ON A CONFIDENTIAL BASIS FOR IDENTIFICATION PURPOSES ONLY. SIZE MULT **TEMPER UNLESS OTHERWISE SPECIFIED** 1. ALL DIMENSIONS IN INCHES [mm] FINISH MATERIAL SPEC No. - TWO PLACE DECIMALS ±0.02 [0.5] FIRST USED ON SCALE - THREE PLACE DECIMALS ±0.005 [0.13] 2:1 DATE DRAWN CHKD APVD BY TJK TJK 4-16-2020 | SRC 28408 03-08-22 PC TJK 05-12-22 05-12-22 SHEET 1 OF PART No. BY APVD REV ECO NUMBER DATE HIGH TEMP POWER JACKS LONG BUSHING RIGHT-ANGLE LOW PROFILE, RoHS L7 RAHLP SERIES DO NOT SCALE DRAWING **REVISIONS** 

SolidWorks CAD File B